

Control and signaling units Ø 30

Harmony 9001K & 9001SK range

Pushbuttons, switches and pilot lights

with double insulated bezel

Complete units 9001SK, with screw clamp terminal



9001SK46J35LYFA

Illuminated selector switches with long handle (super bright LED included)

Shape of head	Supply	Mount on side	Contact block (1)	Contact status 1 - closed 0 - open	Supply voltage V	Number and type of positions	Color	Reference	Weight kg/lb
	Supplied with 24 V light module	1 or 2	9001KA2 		24 ~	2 stay put	Green	9001SK11J35LGFG	0.190/0.419
							Red	9001SK11J35LRFR	0.190/0.419
							Amber	9001SK11J35LYFA	0.190/0.419
		1 or 2	9001KA2 		24 ~	2 spring return from right to left	Green	9001SK34J35LGFG	0.190/0.419
							Red	9001SK34J35LRFR	0.190/0.419
							Amber	9001SK34J35LYFA	0.190/0.419
		1 or 2	9001KA1 		24 ~	3 stay put	Green	9001SK43J35LGFG	0.190/0.419
							Red	9001SK43J35LRFR	0.190/0.419
							Amber	9001SK43J35LYFA	0.190/0.419
		Side 2	9001KA1 		24 ~	3 stay put	Green	9001SK46J35LGFG	0.190/0.419
							Red	9001SK46J35LRFR	0.190/0.419
		Side 1	9001KA1 				Amber	9001SK46J35LYFA	0.190/0.419
		1 or 2	9001KA1 		24 ~	3 spring return to center	Green	9001SK53J35LGFG	0.190/0.419
							Red	9001SK53J35LRFR	0.190/0.419
							Amber	9001SK53J35LYFA	0.190/0.419
		1 or 2	9001KA1 		24 ~	3 spring return from left to center	Green	9001SK63J35LGFG	0.190/0.419
							Red	9001SK63J35LRFR	0.190/0.419
							Amber	9001SK63J35LYFA	0.190/0.419
		Side 2	9001KA1 		24 ~	4 stay put	Green	9001SK88J35LGFG	0.190/0.419
							Red	9001SK88J35LRFR	0.190/0.419
		Side 1	9001KA1 				Amber	9001SK88J35LYFA	0.190/0.419

Illuminated mushroom head pushbuttons, push-pull, Ø 41/1.61 in. red

Shape of head	Supply	Type of contact			Supply voltage V	Reference	Weight kg/lb
							
		NC I. break	NC	CO			
2 position stay put pushbuttons							
	Direct supply for BA 9s bulb (2)	1	1	—	24 ~	9001SKR9P35RH25	0.226/0.498
					120 ~	9001SKR9P38RH25	0.226/0.498
	Via integral transformer for BA 9s bulb (2)	1	1	—	230 ~	9001SKR9P7RH25	0.226/0.498
3 position pushbuttons (pull: spring return, center: stay put, push: spring return)							
	Direct supply for BA 9s bulb (2)	1	1	—	24 ~	9001SKR8P35RH25	0.226/0.498
					120 ~	9001SKR8P38RH25	0.226/0.498
	Via integral transformer for BA 9s bulb (2)	1	1	—	230 ~	9001SKR8P7RH25	0.226/0.498

(1) Order and install listed contact block for noted contact sequence. Other contact sequences are available.

Please contact our Customer Care Centre.

(2) Incandescent bulb, included.