Control and signalling units Ø 22
Harmony® XB4 metal
Pushbuttons and switches for harsh environment
Selector switches and key switches

Assembly of other products using body/contact assemblies: see page 16


PF106195
ZB4 BD4


PF106199
ZB4 BG0


106554
ZBG 455P


PF100233
ZBG P


PF100232
ZBD D2

Selector switches with standard handle and key switches

Screw clamp terminal connections (Schneider Electric anti-retightening system)

Shape of head	Type of operator	Positions: Number	Positions: Type		Reference	Weight kg
Heads only (IP 66 + IP 69K)						
	Selector switch with standard handle, black	2-position 90°	Stay put		**ZB4 BD2**	0.040
			Spring return from right to left		**ZB4 BD4**	0.045
		3-position ± 45°	Stay put		**ZB4 BD3**	0.040
			Spring return to centre		**ZB4 BD5**	0.040
			Spring return from left to centre		**ZB4 BD7**	0.040
			Spring return from right to centre		**ZB4 BD8**	0.040
	Key switch with key n° 455 *(1) (2)*	2-position 90°	Stay put		**ZB4 BG2**	0.098
					ZB4 BG02	0.098
					ZB4 BG4	0.098
			Spring return from right to left		**ZB4 BG6**	0.098
		3-position ± 45°	Stay put		**ZB4 BG0**	0.098
					ZB4 BG03	0.098
					ZB4 BG04	0.098
					ZB4 BG3	0.098
					ZB4 BG5	0.098
					ZB4 BG9	0.098
					ZB4 BG09	0.098

Heads with black metal bezel

For heads with standard black handle only. To order, add the suffix **7** to the references selected from above.
Example: **ZB4 BD2** becomes **ZB4 BD27**.

Replacement keys

Description	Key number	Reference	Weight kg
Keys for booted selector switches			
Sets of 2 keys, one of which supplied booted (rubber boot)	455	**ZBG 455P**	–
	421E	**ZBG 421EP**	–
	458A	**ZBG 458AP**	–
	520E	**ZBG 520EP**	–
	3131A	**ZBG 3131AP**	–

Accessory for key switches *(3)*

Description	Function	Reference	Weight kg
Keyhole cover (rubber cover)	Protection of lock barrel when no key inserted in lock	**ZBG P**	0.005

Boot for standard handle

Description	For use with	Sold in lots of	Unit reference	Weight kg
Boot for standard handle	**ZB4 BD●**	5	**ZBD D2**	0.005

(1) The symbol ⚷ indicates key withdrawal position(s).
(2) For specific keys with other numbers, please consult your Customer Care Centre.
(3) Not compatible with products with key TEC10.